

Tech specs

EN54 LINE

EN54 FireProtect (Heat) Jeweller

Wireless addressable point heat detector



Device compatibility

Check

Communication

Jeweller communication technology

Proprietary wireless communication technology to transmit commands, alarms, and events.

Key features:

- Two-way communication.
- Advanced sabotage protection.
- Block encryption featuring a dynamic key.
- Instant notifications.
- Remote control and configuration in Ajax apps.

Learn more [>](#)

Frequency bands

866.0–866.5 MHz

868.0–868.6 MHz

868.7–869.2 MHz

905.0–926.5 MHz

915.85–926.5 MHz

921.0–922.0 MHz

Depends on the sales region.

Maximum effective radiated power (ERP)

up to 20 mW

Automatic power control to reduce power consumption and radio interference.

Radio signal modulation

GFSK

Radio communication range

up to 1,700 m

Between the device and the control and indicating equipment (CIE) or a range extender in an open space.

Calculate radio communication range at the facility >

Encrypted communication

All stored and transmitted data is protected by block encryption featuring a dynamic key.

Frequency hopping

To prevent radio interference and jamming.

Learn more

Dangerous temperature detection

Sensitive element

2 × thermistor

According to the EN 54-5 requirements for heat detectors of Class A1, B, and C with rate-of-rise (R) and static (S) response types.

Heat sensor modes

- A1, A1R, A1S
- B, BR, BS
- C, CR, CS
- Fixed temperature

For better detection of fire hazards, depending on the installation site of the device. Can be selected in the device settings. Only the following heat sensor modes are compliant with EN 54 requirements: A1R, A1S, BR, BS, CR, and CS.

Additional features

LED indication

- red
- yellow
- green

For indicating detector states: fire alarm, functionality testing, etc.

Installation recommendations

The device is designed for indoor use only.

The SmartBracket mounting panel allows the detector to be rotated up to 90° even after installation.

Sabotage protection

Tamper button

Fault notification when an attempt is made to remove the device from the mounting panel.

[Learn more](#) >

Lock for SmartBracket

to secure the device on the SmartBracket mounting panel

When locked, the lock secures the device and prevents it from being removed without a special tool.



Protection against spoofing

device authentication

Connection loss detection

after 36 s

Detection time depends on **Jeweller** settings.

Power supply

Battery

2 × CR123A

Pre-installed.

Tool-free battery replacement

To replace the batteries, open the lids of the battery compartments.



Reverse polarity protection

Prevents device damage if the batteries are put in incorrectly.

Recommended battery type

Huidrui CR123A; 3 V; 1,600 mAh,
 LiMnO_2

Calculated battery life

up to 6 years

Enclosure

Dimensions

124 × 124 × 48 mm

Weight

265 g

Operating temperature range

from 0 °C to +50 °C

Operating humidity

up to 80%

Protection class

IP20

Flammability rating

UL 94 V-0



Color

Black

White



Complete set

EN54 FireProtect (Heat) Jeweller

SmartBracket mounting panel

2 × CR123A battery (pre-installed)

Installation kit

Quick start guide

Revision

2

Certification and compliance with standards



EN54 FireProtect (Heat) Jeweller



Additional information

Compliance with standards

[Learn more](#) >

User manual

[Learn more](#) >

Warranty

24 months

[Learn more](#) >

Subscribe

Subscribe to our emails about secure life. No spam.

[Subscribe](#)

Request extra help

 +447451279411

 support@ajax.systems

 [@AjaxSystemsSupport_Bot](https://twitter.com/AjaxSystemsSupport_Bot)

 [Send a request](#)



Rating 4.8

4,500,000

people worldwide under Ajax protection

 [Suggest a feature](#)



Products

Intrusion protection

Video surveillance

Fire and life safety

Comfort and automation

All products

Services

System integrations

Ajax Ready products

Fibra wired protocol

Ajax radio protocols

Solutions

Customer stories

Solutions by facility type

Commercial fire detection and alarm system

Wireless Grade 3 solution

Video surveillance solution

Integration with Yale smart locks

Upgrades and retrofits

Why Ajax

How it works

Software

Ajax Security System

Ajax PRO: Tool for Engineers

Ajax Desktop

Ajax PRO Desktop

Ajax TV

Ajax Translator PRO

Ajax Cloud Signaling

Scenarios



Available on
App Store



Available on
Google Play

Support

Manuals and articles

Compliance with standards

Tools

Ajax kit configurator

Ajax device compatibility

CMS software compatibility

Ajax Services availability

Video storage calculator

Video device calculator

Battery life calculator

Radio communication range calculator

Switches and outlets configurator

Fibra power supply calculator

All web tools

Monitoring solutions and integrations

Intrusion alarm monitoring

Video monitoring and visual alarm verification

[Audio alarm verification](#)

Company

[Blog](#)
[About us](#)
[Press page](#)
[Events](#)
[Career](#)
[Ajax Next](#)
[Reviews and feedback](#)

For partners

[For partners](#)
[Ajax Academy](#)
[Partner Portal](#)

[!\[\]\(9ea682cef02bbbdc0191f78cdae1d433_img.jpg\) United Kingdom](#) [Privacy policy](#) [Report a vulnerability](#) [GDPR White Paper](#) [NDAA Statement](#) [Cookie policy](#)
[Anti-Spam Policy](#) [Ajax Services T&C](#) [End user agreement](#) [Warranty](#)

© 2026 AJAX SYSTEMS CH. All rights reserved